

## Features


- Up to 10W CW output power from a 200  $\mu\text{m}$  core fiber
- High Quality, Reliability, & Performance

## Applications

- Defense
- Fiber Lasers
- Medical
- Material Processing
- Solid State Pumping

## Product Specifications

### 975nm Multi-Mode Laser High-Heat-Load Modules w/ Fiber Pigtailed Package



## Description

High brightness, high quality, and high reliability are the foundation of our multi mode product line. Sheaumann's 975nm multi mode laser diodes are available with up to 10W of continuous output power from a 9-pin high-heat-load module. All modules come standard with an internal thermistor, TEC, and photodiode. Output power comes with 200  $\mu\text{m}$  core diameter and is 0.22NA. Sheaumann's trademark laser chip design creates un-measurable degradation and long lifetimes that make our chips among the most reliable in the industry today. All modules come standard with a SMA connector. Our 975nm multi mode line serves a broad range of applications including solid state pumping, fiber lasers, material processing, graphics, medical, and defense.

Please view our website for mechanical drawings of our different packaging options.

### Performance Data for 808nm Multi-Mode HHL Fiber Modules

Parameter	Unit	4.5W Series			7.5W Series			10W Series		
		Min	Typ	Max	Min	Typ	Max	Min	Typ	Max
Wavelength	nm	970	975	980	970	975	980	970	975	980
Spectrum FWHM	nm	-	3	5	-	3	5	-	3	5
Operating Power ( $P_o$ )	W	-	4.5	-	-	7.5	-	-	10	-
Operating Current ( $I_o$ )	A	-	6.9	7.7	-	14.0	15.2	-	16.0	17.0
Operating Voltage ( $V_o$ )	V	-	1.8	2.5	-	1.8	2.5	-	2.5	2.8
Lifetime	hour	10,000	-	-	10,000	-	-	10,000	-	-
Threshold ( $I_{th}$ )	A	-	0.50	0.80	-	1.5	1.8	-	1.0	1.2
Slope Efficiency (dP/dI)	W/A	0.65	0.70	-	0.50	0.60	-	0.63	0.68	-
TEC Voltage	V	-	-	8.6	-	-	8.6	-	-	8.6
TEC Current	A	-	-	3.8	-	-	3.8	-	-	3.8
Storage Temperature	$^{\circ}\text{C}$	-40	-	80	-40	-	80	-40	-	80
Operating Temperature ( $T_{op}$ )	$^{\circ}\text{C}$	0	25	50	0	25	55	0	25	55
Lead Soldering Temperature (5 sec)	$^{\circ}\text{C}$	-	-	250	-	-	250	-	-	250


**Note:** Specifications are subject to change without notice. All Sheaumann Laser products are TE polarized

**Power Output  
Danger Label**



**WARNING!**

Invisible laser radiation is emitted from devices as shown below



**21 CFR 1040.10  
Compliance**

Because of the small size of these devices, each of the labels shown are attached to the individual shipping container. They are illustrated here to comply with 21 CFR 1040.10 as applicable under the Radiation Control for Health and Safety Act of 1968.

**Product Performance Data Graphs**

**Determining Your Product number**

MM—WWW—PPPP—XYZ—(custom add-ons)  
(package)-(wavelength)-(power)-(options)

<b>Package:</b>	<b>X Option (aperture size)</b>
HW HHL package (9pin, fiber, TEC, PD, Thermistor)	2 200µm fiber
<b>Wavelength:</b>	<b>Y Option (wavelength tolerance)</b>
975 975nm	5 ±5nm
<b>Power Options:</b>	<b>Z Option (additional options)</b>
4500 4.5W 7500 7.5W 010W 10W	C SMA Connector

**Standard Product  
Configurations**

- 4W Series**  
HW-975-4500-25C
- 7.5W Series**  
HW-975-7500-25C
- 10W Series**  
HW-975-010W-25C

Please note: These are our standard product configurations. Other options may be available, please inquire about any additional options that you may require when contacting our Sales Team.

**Safety**

Caution: Laser light emitted from any diode laser is invisible and may be harmful to the human eye. Avoid looking directly into the diode laser aperture when the device is in operation. **Note:** The use of optical instruments with this product will increase eye hazard.

**ESD Caution**

Always handle diode lasers with extreme care to prevent electrostatic discharge, the primary cause of unexpected diode failure. You can prevent ESD by always wearing wrist straps, grounding all applicable work surfaces, and following extremely rigorous anti-static techniques when handling

**Operating Considerations**

Operating the diode laser outside of its maximum ratings may cause device failure or a safety hazard. Power supplies used with the component must be employed such that the maximum peak optical power cannot be exceeded. CW diode lasers may be damaged by excessive drive current or switching transients. When using power supplies, the diode laser should be connected with the main power on and the output voltage at zero. The current should be increased slowly while monitoring the diode laser output power and the drive current. Device degradation accelerates with increased temperature, and therefore careful attention to minimize the case temperature is advised. A proper heat-sink for the diode laser on a thermal radiator will greatly enhance laser life.